

NP3151W Installation Guide

Desktop and Ceiling Mount

v 1.6

Contents

Product Description, Lens Specs, Screen/Aspect Ratio	Pg 1
Notes and Formulas	Pg 1
Diagrams & Distance Charts; 4:3	Pg 2
16:9	Pg 3
Lens Shift Adjustable Range	Pg 4
Cabinet Dimensions	Pg 5
Lens Dimensions	Pg 6
Ceiling Mount Dimensions	Pg 7
Ceiling Mount Dimensions (continued)	Pg 8
Input Panel and Control Codes	Pg 9



Product Description

Type:	3 panel LCD projector, 0.74 p-Si TFT w/MLA	Dimensions:	399mm(W) x 150mm(H) x 358mm(D)
Resolution:	1280 x 800 (16:10)	Weight:	7,5 kg
Fan Noise:	38 dB / 31dB @ 1 meter	Brightness:	4000 Lumens
Power Consumption:	490W (max)	BTU's:	1672 BTU/hour
Network Ready, integrated wired and wireless adapter		Manual:	Lens Shift, Horizontal & Vertical /Zoom/ Focus

Lens Specifications

NP01FL:	Throw Ratio: ~ 0.8:1 Screen Sizes: 38"-143"	Focal Length: 13.2mm F/#:2.3	NP03FL:	Throw Ratio: 1.94 - 3.07:1 Screen Sizes: 38" - 476"	Focal Length: 31.6 – 50.2mm F/#:2.2
NP02FL:	Throw Ratio: 1.18 - 1.54:1 Screen Sizes: 29" - 476"	Focal Length: 19.42 - 25.26mm F/#:2.2	NP04FL:	Throw Ratio: 2.98 - 4.77:1 Screen Sizes: 57" - 476"	Focal Length: 48.8 - 77.6mm F/#:2.2
Standard:	Throw Ratio: 1.5 - 2.0:1 Screen Sizes: 29" – 476"	Focal Length: 24.4 - 32.5mm F/#:1.7	NP05FL:	Throw Ratio: 4.62 - 7.02:1 Screen Sizes: 57" - 476"	Focal Length: 76.6 - 116.5mm F/#:2.2

Screen/Aspect Ratio

16:10, 16:9 and 4:3 screens are fully supported with proper aspect ratio control for both type sources using NEC developed scaling technology. Menu selections have settings for each screen type and aspect ratio control for each source type.

Notes

- For screen sizes not indicated on the projection tables, use the formulas below.
- If the figures on the tables do not match the results of formulas, use the figures in the table.
- All calculations are based on 4:3 aspect ratio.
- Distances may vary $\pm 5\%$.

Formulas

The Projection Formulas use the image width for calculation. Image width is the same for all aspect ratios, only vertical image size varies. For proper projector placement, determine the image width for a desired screen size. Use the Screen Formulas below to calculate all screen dimensions. Plug in the image width for "W" in the Projection Formulas.

Refer to the diagrams and charts for popular screen sizes on page 2 and 3:

Projection Formulas:

NP01FL:	$C = 0.8325W - 1.33$
NP02ZL:	$C(\text{Wide}) = 1.2220W - 1.798$ ----- $C(\text{Tele}) = 1.5894W - 1.795$
Standard:	$C(\text{Wide}) = 1.5455W - 2.022$ ----- $C(\text{Tele}) = 2.0555W - 2.015$
NP03ZL:	$C(\text{Wide}) = 2.0069W - 2.830$ ----- $C(\text{Tele}) = 3.1710W - 2.840$
NP04ZL:	$C(\text{Wide}) = 3.0537W - 4.830$ ----- $C(\text{Tele}) = 4.8860W - 4.850$
NP05ZL:	$C(\text{Wide}) = 4.8275W - 7.625$ ----- $C(\text{Tele}) = 7.3379W - 7.645$

Definitions:

W = Image Width
H = Image Height (size)
C = Throw distance

4:3 Screen Formulas:

$W = H \times 4/3$
 $H = W \times 3/4$
Diagonal = $W \times 5/4$

16:9 Screen Formulas:

$W = H \times 16/9$
 $H = W \times 9/16$
Screen Diagonal = $W \times 18.358/16$

Note: Tilting the front of the projector up or down by more than 45° from level could reduce lamp life by up to 20%.

NP3151W Installation Guide

Desktop and Ceiling Mount


v 1.6

Projection Distance and Screen Size for Ceiling Mount

The following shows the proper relative positions of the projector and screen. Refer to the table to determine the position of installation.


Distances are in inches. For millimeters multiply by 25.4. (← bitte löschen, wenn Bemaßung in "mm" geändert ist)

Ceiling Mount Installation



Desktop Installation

Note: Lens shift feature is not available with NP01FL (rear lens) NP01FL should be used only for "zero degree" / "no-offset" applications.



Distance Chart for popular 4:3 screens

Screen Size (4:3)			Rear Lens	Zoom Lenses									
			NP01FL	Standard		NP02ZL		NP03ZL		NP04ZL		NP05ZL	
Diagonal	Width(W)	Height (H)	0.8:1	1.5 - 2.0:1		1.18 - 1.54:1		1.94 - 3.07:1		2.98 - 4.77:1		4.62 - 7.02:1	
inches	inches	inches	inches	inches		inches		inches		inches		inches	
40	32	24	25.38	47.37 - 63.8		37.3 - 49.07		61.4	98.6	NA		NA	
60	48	36	38.7	72.11 - 96.6		56.9 - 74.5		93.5	149.4	141.7	229.7	NA	NA
67	53.6	40.2	43.3	80.8 - 108.2		63.7 - 83.4		104.7	167.1	158.8	257.0	NA	NA
72	57.6	43.2	46.6	86.9 - 116.4		68.6 - 89.8		112.8	179.8	171.1	276.6	NA	NA
84	67.2	50.4	54.6	101.8 - 136.1		80.3 - 105.0		132.0	210.3	200.4	323.5	316.8	485.5
90	72	54	58.6	109.2 - 146.0		86.2 - 112.6		141.7	225.5	215.0	346.9	340.0	520.7
100	80	60	65.2	121.6 - 162.4		95.96 - 125.4		157.7	250.8	239.5	386.0	378.6	579.4
120	96	72	78.5	146.3 - 195.3		115.5 - 150.8		189.8	301.6	288.3	464.2	455.8	696.8
150	120	90	98.46	183.4 - 244.6		144.8 - 188.9		238.0	377.7	361.6	581.5	571.7	872.9
180	144	108	NA	220.5 - 294.0		174.2 - 227.1		286.2	453.8	434.9	698.7	687.5	1049.0
210	168	126	NA	257.6 - 343.3		203.5 - 265.2		334.3	529.9	508.2	816.0	803.4	1225.1
240	192	144	NA	294.7 - 392.6		232.8 - 303.4		382.5	606.0	581.5	933.3	919.3	1401.2
270	216	162	NA	331.8 - 442.0		262.2 - 341.5		430.7	682.1	654.8	1050.5	1035.1	1577.3
300	240	180	NA	368.9 - 491.3		291.5 - 379.7		478.8	758.2	728.1	1167.8	1151.0	1753.5
400	320	240	NA	492.6 - 655.7		389.2 - 506.8		639.4	1011.9	972.4	1558.7	1537.2	2340.5
500	400	300	NA	616.30 - 820.2		487.0 - 634.0		799.9	1265.6	1216.7	1949.6	1923.4	2927.5

Note: For screen sizes not indicated on the projection tables, use the formulas on page 1.

NP3151W Installation Guide

Desktop and Ceiling Mount


v 1.6

Projection Distance and Screen Size for Ceiling Mount

The following shows the proper relative positions of the projector and screen. Refer to the table to determine the position of installation.


Distances are in inches. For millimeters multiply by 25.4. (← bitte löschen, wenn Bemaßung in "mm" geändert ist)

Ceiling Mount Installation



Desktop Installation

Note: Lens shift feature is not available with NP01FL (rear lens) NP01FL should be used only for "zero degree" / "no-offset" applications.



Distance Chart for popular 16:9 screens

Screen Size (16:9)			Rear Lens	Zoom Lenses									
			NP01FL	Standard	NP02ZL		NP03ZL		NP04ZL		NP05ZL		
Diagonal	Width(W)	Height (H)	0.8:1	1.5 - 2.0:1	1.18 - 1.54:1		1.94 - 3.07:1		2.98 - 4.77:1		4.62 - 7.02:1		
inches	inches	inches	inches	inches	inches		inches		inches		inches		
92	80	45	65,24	121,6 - 162,4	96,0 - 125,4	157,7	250,8	239,5	386,0	366,4	579,4		
100	87	49	71,1	132,4 - 176,8	104,5 - 136,5	171,8	273,0	260,8	420,2	399,5	630,8		
106	92	52	75,2	140,1 - 187,1	110,6 - 144,4	181,8	288,9	276,1	444,7	423,1	667,4		
110	96	54	78,5	146,3 - 195,3	115,5 - 150,8	189,8	301,6	288,3	464,2	442,0	696,8		
119	104	58,8	85,2	158,7 - 211,8	125,3 - 163,5	205,9	326,9	312,8	503,3	494,4	755,5		
123	107	60	87,7	163,3 - 217,9	129,0 - 168,3	211,9	336,5	321,9	518,0	508,9	777,5		
133	116	65	95,1	177,2 - 236,4	140,0 - 182,6	230,0	365,0	349,4	561,9	552,4	843,6		
135	118	66	96,8	180,3 - 240,5	142,4 - 185,8	234,0	371,3	355,5	571,7	562,0	858,2		
159	139	78	NA	212,8 - 283,7	168,1 - 219,1	276,1	437,9	419,6	674,3	663,4	1012,3		
161	140	79	NA	214,3 - 285,8	169,3 - 220,7	278,1	441,1	422,7	679,2	668,2	1019,7		
229	200	113	NA	307,1 - 409,1	242,6 - 316,1	398,6	631,4	605,9	972,4	957,9	1459,9		
275	240	135	NA	368,9 - 491,3	291,5 - 379,7	478,8	758,2	728,1	1167,8	1151,0	1753,5		
367	320	180	NA	492,6 - 655,7	389,2 - 506,8	639,4	1011,9	972,4	1558,7	1537,2	2340,5		
459	400	225	NA	616,3 - 820,2	487,0 - 634,0	799,9	1265,6	1216,7	1949,6	1923,4	2927,5		



Note: For screen sizes not indicated on the projection tables, use the formulas on page 1.

NP3151W Installation Guide

Desktop and Ceiling Mount

v 1.6

Lens Shift Adjustable Range



Lens Shift Range for Desktop and Ceiling Mount Application

The diagram below shows the location of the image position in the lens. The lens can be shifted within the shaded area as shown using the normal projection position as a starting point.

Note: Lens shift feature is not available with NP01FL (rear lens). NP01FL should be used only for "zero degree" / "no-offset" applications.

Maximum Possible Range for Standard Lens/NP02ZL/NP03ZL/NP04ZL/NP05ZL:

Up: 0.5V

Right: 0.10H

Left: 0.10H

(H: width of projected image, V: height of projected image)

NP3151W Installation Guide


Desktop and Ceiling Mount

v 1.6

Cabinet Dimensions

The following diagrams show the cabinet dimensions for the NP3150.

Dimensions are in inches. For millimeters multiply by 25.4. (← bitte löschen, wenn Bemaßung in "mm" geändert ist)



NP3151W Installation Guide


Desktop and Ceiling Mount

v 1.6

Lens Dimensions

The following drawings show the added dimensions for the optional lenses

Dimensions are in inches. For millimeters multiply by 25.4. (← bitte löschen, wenn Bemaßung in "mm" geändert ist)



NP3151W Installation Guide


Desktop and Ceiling Mount

v 1.6


Optional Ceiling Mount Dimensions (Model #: NP05CM)

The following diagrams show ceiling mount dimensions for the NP3150.

Fixed Ceiling Part and Lens Center Dimensions Diagram



Fixed Ceiling Part Bolt Hole Position Dimensions




NP3151W Installation Guide

Desktop and Ceiling Mount

v 1.6


Optional Ceiling Mount Dimensions (Model #: NP05CM) (continued)

The following diagrams show ceiling mount dimensions for the NP3150.



⚠ WARNING!

The use of screws other than those supplied for mounting purposes may cause the projector to be damaged or fall and cause injury. Please be sure to use the supplied screws.



For further information, please read the "Installation and Adjustment Manual" of NP05CM

NP3151W Installation Guide

Desktop and Ceiling Mount

v 1.6

Input / Output Panel




PC Control Codes

Function	Code Data
POWER ON	02H 00H 00H 00H 00H 02H
POWER OFF	02H 01H 00H 00H 00H 03H
INPUT SELECT RGB 1	02H 03H 00H 00H 02H 01H 01H 09H
INPUT SELECT RGB 2	02H 03H 00H 00H 02H 01H 02H 0AH
INPUT SELECT VIDEO 1	02H 03H 00H 00H 02H 01H 06H 0EH
INPUT SELECT VIDEO 2	02H 03H 00H 00H 02H 01H 07H 0FH
INPUT SELECT S-VIDEO	02H 03H 00H 00H 02H 01H 0BH 13H
INPUT SELECT DVI (DIGITAL)	02H 03H 00H 00H 02H 01H 1AH 22H
INPUT SELECT DVI (ANALOG)	02H 03H 00H 00H 02H 01H 03H 0BH
INPUT SELECT NETWORK	02H 03H 00H 00H 02H 01H 1FH 27H
PICTURE MUTE ON	02H 10H 00H 00H 00H 12H
PICTURE MUTE OFF	02H 11H 00H 00H 00H 13H
SOUND MUTE ON	02H 12H 00H 00H 00H 14H
SOUND MUTE OFF	02H 13H 00H 00H 00H 15H
ON SCREEN MUTE ON	02H 14H 00H 00H 00H 16H
ON SCREEN MUTE OFF	02H 15H 00H 00H 00H 17H

Cable Connection

Communication Protocol:

Baud Rate: 38400 bps (for cable lengths longer than 20', it is recommended changing to 9600 bps in setup menu)
 Data Length: 8 bits
 Parity: No Parity
 Stop Bit: One bit
 X on/off: None
 Communications: Full duplex



PC Control Connector (D-Sub 9P)

NOTE: Pins 1, 4, 6, and 9 are used inside the projector.

Jumper "Request to send" and "Clear to Send" together on both ends of the cable to simplify cable connection.